

AA-6600

SOLID STATE FM / AM MULTIPLEX TUNER AMPLIFIER



- SPEAKER SELECTOR ■ FM CENTER TUNING METER
- FM/AM STRENGTH SIGNAL METER
- SPEAKER SYSTEM SELECTOR

SPECIFICATIONS

Tuner Section(FM)

Frequency Range: 88 to 108 MHz

Sensitivity: $2.0\mu\text{V}$ (IHF)

S/N Ratio: Better than 60 dB

Selectivity: Better than 50 dB

Tuner Section(AM)

Frequency Range: 535 to 1,605 kHz

Sensitivity(IHF): $20\mu\text{V}$ at 1 MHz

S/N Ratio: Better than 45 dB

Selectivity: Better than 20 dB

Amplifier Section:

Frequency Response: 20 to 50,000 Hz (-3 dB)

Output Power: 120W at music power

Dimensions: 17-1/2"(W) × 5-1/4"(H) × 13-3/8"(D) (445 × 133 × 340 mm)

Weight: 24.4 lbs(11 kg)